



Lochinvar®

208 Volt 3 Phase to 480 Volt 3 Phase Step Up Transformer

Submittal Sheet **STEP UP TRANSFORMER-
SUB-05**

208 VOLT 3 PHASE TO 480 VOLT 3 PHASE STEP UP TRANSFORMER

Job Name: _____

Location: _____

Engineer: _____

Agent/Wholesaler: _____

Contractor: _____

NOTES:

208 VOLT 3 PHASE TO 480 VOLT 3 PHASE STEP UP TRANSFORMER

DIMENSIONS & SPECIFICATIONS

Part Number	Used on Models	480V 3PH RLA	FLA Fan & Pump	FLA Unit	MCA	MOCP	208V 3PH RLA	FLA Fan & Pump	FLA Unit	MCA	MOCP	Height	Width	Depth	Weight (lbs)
100371007	AHP060	13	3.9	16.9	20.2	35	30	9	39	46.5	80	29	26	24	298
100371008	AHP140	28	3.9	31.9	38.9	70	64.6	9	73.6	89.8	175	29	26	24	326
100379062	AHP200	41	7.8	48.8	59.1	100	94.6	18	112.6	136.4	250	29	26	24	375
100371009	AHP280	56	7.8	63.8	77.8	150	129.2	18	147.2	179.5	325	36	28	27	445
100379063	AHP350	69	11.7	80.7	97.8	175	159.2	27	186.2	226	400	36	28	27	770

*Information subject to change without notice. Dimensions shown are approximate and should not be used for construction purposes. Dimensions are in inches.



LEGEND

RLA: Rated Load Amps

FLA: Full Load Amps

MCA: Maximum Current Ampacity

MOCP: Minimum Overcurrent Protection



Lochinvar, LLC
300 Maddox Simpson Parkway
Lebanon, Tennessee 37090
P: 615.889.8900 / F: 615.547.1000
f in @ Lochinvar.com

DESIGNED ★ ENGINEERED ★ ASSEMBLED
USA